

rp-pppoe

- /rp-pppoe/configs/pppoe.conf
 - 69 CONNECT_TIMEOUT=0

```
64 # 如果您在物理上无法访问的主机上使用 rp-pppoe, 请设置
65 # CONNECT_TIMEOUT 为 0。这确保机器不断尝试
66 # 在调用 pppoe-start 后永久连接。否则会
67 # 在 CONNECT_TIMEOUT 秒后发出并且不会尝试
68 # 再次连接, 使其无法访问。
69 CONNECT_TIMEOUT=30
```

```
#####
#
# pppoe.conf
#
# Configuration file for rp-pppoe.  Edit as appropriate and install in
# /etc/ppp/pppoe.conf
#
# NOTE: This file is used by the pppoe-start, pppoe-stop, pppoe-connect and
#       pppoe-status shell scripts.  It is *not* used in any way by the
#       "pppoe" executable.
#
# Copyright (C) 2000 Roaring Penguin Software Inc.
#
# This file may be distributed under the terms of the GNU General
# Public License.
#
# LIC: GPL
# $Id$
#####

# When you configure a variable, DO NOT leave spaces around the "=" sign.

# Ethernet card connected to DSL modem
ETH=eth0

# PPPoE user name.  You may have to supply "@provider.com"  Sympatico
# users in Canada do need to include "@sympatico.ca"
```

```
# Sympatico uses PAP authentication.  Make sure /etc/ppp/pap-secrets
# contains the right username/password combination.
# For Magma, use xxyyzz@magma.ca
USER=02368109376

# Bring link up on demand?  Default is to leave link up all the time.
# If you want the link to come up on demand, set DEMAND to a number indicating
# the idle time after which the link is brought down.
DEMAND=no
#DEMAND=300

# DNS type: SERVER=obtain from server; SPECIFY=use DNS1 and DNS2;
# NOCHANGE=do not adjust.
DNSTYPE=SERVER

# Obtain DNS server addresses from the peer (recent versions of pppd only)
# In old config files, this used to be called USEPEERDNS.  Changed to
# PEERDNS for better Red Hat compatibility
PEERDNS=no

DNS1=
DNS2=

# Make the PPPoE connection your default route.  Set to
# DEFAULTROUTE=no if you don't want this.
DEFAULTROUTE=no

### ONLY TOUCH THE FOLLOWING SETTINGS IF YOU' RE AN EXPERT

# How long pppoe-start waits for a new PPP interface to appear before
# concluding something went wrong.  If you use 0, then pppoe-start
# exits immediately with a successful status and does not wait for the
# link to come up.  Time is in seconds.
#
# WARNING WARNING WARNING:
#
# If you are using rp-pppoe on a physically-inaccessible host, set
# CONNECT_TIMEOUT to 0.  This makes SURE that the machine keeps trying
# to connect forever after pppoe-start is called.  Otherwise, it will
# give out after CONNECT_TIMEOUT seconds and will not attempt to
# connect again, making it impossible to reach.
```

```
CONNECT_TIMEOUT=30
```

```
# How often in seconds pppoe-start polls to check if link is up
```

```
CONNECT_POLL=2
```

```
# Specific desired AC Name
```

```
ACNAME=
```

```
# Specific desired service name
```

```
SERVICENAME=
```

```
# Character to echo at each poll. Use PING="" if you don't want
```

```
# anything echoed
```

```
PING="."
```

```
# File where the pppoe-connect script writes its process-ID.
```

```
# Three files are actually used:
```

```
# $PIDFILE contains PID of pppoe-connect script
```

```
# $PIDFILE.pppoe contains PID of pppoe process
```

```
# $PIDFILE.pppd contains PID of pppd process
```

```
CF_BASE=`basename $CONFIG`
```

```
PIDFILE="/var/run/$CF_BASE-pppoe.pid"
```

```
# Do you want to use synchronous PPP? "yes" or "no". "yes" is much
```

```
# easier on CPU usage, but may not work for you. It is safer to use
```

```
# "no", but you may want to experiment with "yes". "yes" is generally
```

```
# safe on Linux machines with the n_hdlc line discipline; unsafe on others.
```

```
SYNCHRONOUS=no
```

```
# Do you want to clamp the MSS? Here's how to decide:
```

```
# - If you have only a SINGLE computer connected to the DSL modem, choose
```

```
# "no".
```

```
# - If you have a computer acting as a gateway for a LAN, choose "1412".
```

```
# The setting of 1412 is safe for either setup, but uses slightly more
```

```
# CPU power.
```

```
CLAMPMSS=1412
```

```
#CLAMPMSS=no
```

```
# LCP echo interval and failure count.
```

```
LCP_INTERVAL=20
```

```
LCP_FAILURE=3
```

```
# PPPOE_TIMEOUT should be about 4*LCP_INTERVAL
PPPOE_TIMEOUT=80

# Firewalling: One of NONE, STANDALONE or MASQUERADE
FIREWALL=NONE

# Linux kernel-mode plugin for pppd.  If you want to try the kernel-mode
# plugin, use LINUX_PLUGIN=/etc/ppp/plugins/rp-pppoe.so
LINUX_PLUGIN=

# Any extra arguments to pass to pppoe.  Normally, use a blank string
# like this:
PPPOE_EXTRA=""

# Rumour has it that "Citizen's Communications" with a 3Com
# HomeConnect DSL Modem DualLink requires these extra options:
# PPPOE_EXTRA="-f 3c12:3c13 -S ISP"

# Any extra arguments to pass to pppd.  Normally, use a blank string
# like this:
PPPD_EXTRA=""

##### DON' T CHANGE BELOW UNLESS YOU KNOW WHAT YOU ARE DOING
# If you wish to COMPLETELY override the pppd invocation:
# Example:
# OVERRIDE_PPPD_COMMAND="pppd call dsl"

# If you want pppoe-connect to exit when connection drops:
# RETRY_ON_FAILURE=no
```

Revision #1

Created 28 July 2022 15:46:34 by

Updated 29 July 2022 11:37:20 by